



Main

| | |
|---------------------------|----------------------|
| Product or Component Type | Full voltage starter |
| Range of Product | Instakits |
| Motor starter type | Non reversing |

Complementary

| | |
|-----------------------------------|---|
| [Ue] rated operational voltage | 120 V AC 50/60 Hz |
| [Ie] rated operational current AC | 25 A |
| Maximum Horse Power Rating | 0.5 Hp 120 V AC, 1 phase 2 Hp 240 V AC, 1 phase 3 Hp 208 V AC, 3 phase 3 Hp 230 V AC, 3 phase 7.5 Hp 460 V AC, 3 phase 10 hp 575 V AC, 3 phase |
| [Uc] control circuit voltage | 600 V AC |
| Auxiliary contact composition | 1 NO + 1 NC |
| Location of connection | Line |

Environment

| | |
|---------------------------|--------------------------|
| Product Certifications | UL[RETURN]CSA[RETURN]IEC |
| NEMA degree of protection | NEMA 1 steel |

Offer Sustainability

| | |
|----------------------------|---|
| Sustainable offer status | Green Premium product |
| REACH Regulation | REACH Declaration |
| REACH free of SVHC | Yes |
| EU RoHS Directive | Compliant EU RoHS Declaration |
| Toxic heavy metal free | Yes |
| Mercury free | Yes |
| China RoHS Regulation | China RoHS Declaration |
| RoHS exemption information | Yes |
| Circularity Profile | No need of specific recycling operations |
| PVC free | Yes |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.