



## BIPC4/010S, Insulation Piercing Connector for Cu/Al, Run: #3-4/0, Tap: #10-#2

By Burndy  
Catalog # [BIPC4/010S](#)



Insulation Piercing Connector for Copper and Aluminum, Run: #3-4/0, Tap: #10-#2, ideal for splicing, tapping and dead-ending aluminum and copper conductor with shearing installation technology. 6-point socket impact driver for easy installation and removal, no torque wrench required.

### Features

- Flexibility! One connector allows for tap, splice or dead-end configurations
- Time Savings! Requires no cable stripping, conductor brushing, inhibitor application or after installation taping
- Engineered shear bolt technology applies consistent torque for efficient and reliable connectors
- Easy installation and removal - only requires 6-point socket impact driver
- cULus Listed Splicing Wire Connector, AL9CU Rated, for copper and aluminum conductor combinations up to 90 degrees C, \*600 Volt applications
- Insulation piercing design for use in multiple applications - overhead covered and bare taps, service and metering connections, and lighting system work

### General

Application - For Use On Copper and Aluminum  
Catalog Number BIPC4/010S

UPC 621945653009

### Certifications And Compliance

Buy American Compliant Certified Listed  
Contact Manufacturer TAA Compliant (All status valid till December 2024)

### Logistics

Carton Quantity 12  
Pallet Quantity 1080

### Product Assets

[Catalogs - BURNDY Master Catalog - Section A - Mechanical](#)  
[Catalogs - BURNDY Master Catalog - Full Line BURNDY Catalog](#)  
[Installation Manuals - Overhead Secondary Networks Insulation Piercing Connector BIPC](#)  
[Interactive Catalog - BURNDY Full-Line Digital Catalog](#)  
[Sell Sheets - Insulation Piercing Connector for Cu/AL](#)  
[Specifications - BIPC4/010S](#)