

QMQB Panelboards - Selection Table

QMQB Bases

Total Branch Breaker Height (X Units)	3 Phase 3 Wire					3 Phase 4 Wire				
	Maximum Main Bus Capacity					Maximum Main Bus Capacity				
	225A	400A	600A	800A	1200A	225A	400A	600A	800A	1200A
36X	—	—	QMQB-0612T3	—	—	—	—	QMQB-0612T4	—	—
40X	QMQB-0212T3	QMQB-0412T3	—	—	—	QMQB-0212T4	QMQB-0412T4	—	—	—
44X	—	—	—	—	QMQB-1232T3	—	—	—	—	QMQB-1232T4
56X	—	—	—	QMQB-0832T3	—	—	—	—	QMQB-L0832T4	—
60X	—	—	QMQB-0632T3	—	—	—	—	QMQB-0632T4	—	—
64X	QMQB-0232T3	QMQB-0432T3	—	—	—	QMQB-0232T4	QMQB-0432T4	—	—	—
68X	—	—	—	—	QMQB-1252T3	—	—	—	—	QMQB-1252T4
80X	—	—	—	QMQB-0852T3	—	—	—	—	QMQB-0852T4	—
84X	—	—	QMQB-0652T3	—	—	—	—	QMQB-0652T4	—	—
88X	QMQB-0252T3	QMQB-0452T3	—	—	—	QMQB-0252T4	QMQB-0452T4	—	—	—

Notes:

1. Service Entrance Available, consult Schneider Canada. Requires additional 2X of branch switch height.
2. Ground lugs not included.
3. QMQB panels include required filler plates.
4. For copper bus, consult Schneider Canada.



30A: 30A (TWIN)



200A (SINGLE)

QMQB Switches (Three Pole Only)

Max. Volts	Amps	Catalogue Number	Wire Size	Branch Height	Fuse Type	AIC Rating	Poles	Connector Mounting Hardware	List Price ‡
600 Vac 250 Vdc	30-30	QMQB3336C	(1) #14-#6 Cu/Al	8X	J, T (100A Only)	200kA (J, T Fuse)	3	CKBH-QMQB	
	60-60	QMQB6636C	(1) #12-#2 (Al) or (1) #14-#2 (Cu)						
	100-100	QMQB1136C	(1) #12-1/0 (Al) or (1) #14-1/0 (Cu)						
	30-60	QMQB3636C	Refer to twin unit						
	30-100	QMQB3136C							
	60-100	QMQB6136C							
	200	QMQB2036C	(1) #6-250MCM Cu/Al	14X	H, R, J, T	10kA (R Fuse) 100kA (J, T Fuse)	3	QMQB200CMH	
	200	QMQB2036B		200kA (R, J, T Fuse)		QMQB200CMH			
	400	QMQB4836C	(1) 1/0-750MCM or (2) 1/0-500MCM or (3) 1/0-250MCM or (4) 1/0-3/0 Cu/Al	24X	H, R, J, T	10kA (R Fuse) 100kA (J, T Fuse)	3	QMQB400CMH	
	400	QMQB4836B				200kA (R, J, T Fuse)			QMQB400CMH
	600	QMQB7036C				10kA (R Fuse) 100kA (J, T Fuse)			QMQB600CMH
	600	QMQB7036B				200kA (R, J, T Fuse)			QMQB600CMH
	800	QMQB8836C	(2) 1/0-750MCM or (3) 1/0-500MCM Cu/Al	28X	L, T	100kA (L, T Fuse)	3	QMQB800CMH	
	800	QMQB8836B				200kA (L, T Fuse)			QMQB800CMH

Notes:

1. See Section E for fuses.
2. 30A to 600A units are shipped in class J fuse configuration. Please specify when class T fuse is required (not available for 30A and 60A).
3. 800A units are shipped in Class L configuration. Please specify when Class T fuse is required.