

Product data sheet

Specifications

SQUARE D



Safety switch lug kit, 100A, series F switch, 6-0 awg Al, 10-0 awg Cu

CL10F

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Product or Component Type	Lug kit
Product destination	Safety switch series F heavy duty 100 A

Complementary

AWG gauge	AWG 10...AWG 1/0 copper AWG 6...AWG 1/0 aluminium
Material	Copper
Tightening torque	50 lbf.in (5.6 N.m) (AWG 3...AWG 1/0) 45 lbf.in (5.08 N.m) (AWG 6...AWG 4) 40 lbf.in (4.5 N.m) (AWG 8) 35 lbf.in (4.0 N.m) (AWG 14...AWG 10)

Ordering and shipping details

Category	US10DE500199
Discount Schedule	0DE5
GTIN	785901932956
Returnability	Yes
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	7.950 in (20.193 cm)
Package 1 Width	2.250 in (5.715 cm)
Package 1 Length	14.300 in (36.322 cm)
Package weight(Lbs)	0.160 oz (4.536 g)

Contractual warranty

Warranty (in months)	18
----------------------	----

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
SCIP Number	Fcbb2f4b-148e-498d-b15c-530db69350d4
EU RoHS Directive	Compliant
REACH Regulation	Free of Substances of Very High Concern above the threshold
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
Take-back	No