



GE  
Lighting

### 35775 - Integrated 2ft LED Glass Tubes

#### LED8ET8/G/2/830

- ☞ Convert your existing linear fluorescent fixture to LED lighting without needing a comprehensive reinstall.
- ☞ Each LED tube is outfitted with an internal GE driver.
- ☞ The GE integrated LED tubes run on electronic T8 instant-start or programmed start ballasts.
- ☞ 66% longer life than LFL (50,000 vs. 30,000 hours)
- ☞ No UV
- ☞ Easy disposal, non-hazardous waste
- ☞ Check ballast compatibility at [www.gelighting.com/LEDTUBES-ballast-compatibility](http://www.gelighting.com/LEDTUBES-ballast-compatibility)

#### Product Photo



#### GENERAL CHARACTERISTICS

Product Technology	LED
Rated Life (Hours)	50000 h
LED Tube Type	Glass
Base	G13
Bulb Shape	T8

#### PHOTOMETRIC CHARACTERISTICS

Nominal Initial Lumen per Watt	1300 lm
Color Rendering Index-CRI	80
Color Temperature	3000 K

#### PRODUCT INFORMATION

Product Code	35775
Description	LED8ET8/G/2/830
Alternative Unit Of Measure	EACH
Standard Package Quantity	20
Ean UPC	043168357753
Standard Package GTIN	00043168357753
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	20
Sales Unit	Each
UCC	043168357753
Alternative Unit Of Measure	CASE
Standard Package Quantity	20
Ean UPC	043168357753
Standard Package GTIN	10043168357750
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	20
Sales Unit	Case
UCC	043168357753

#### DIMENSIONS

Bulb Max Overall Length-MOL	24.0 mm
-----------------------------	---------

#### ELECTRICAL CHARACTERISTICS

Rated power (Watts)	8 W
---------------------	-----

#### CAUTIONS & WARNINGS

##### Caution

##### Risk of fire

Use only in place of fluorescent lamps specified on label

If the lamp or luminaire exhibits undesirable operation, immediately turn off power, remove lamp from luminaire and contact manufacturer

Direct replacement for 17W/24T8 lamps only

Do not install this lamp in a pre-heat luminaire

This lamp only operates on electronic ballasts

If lamp does not light when luminaire is energized, remove lamp from luminaire and contact lamp manufacturer or qualified electrician

##### Risk of electric shock

Suitable for damp locations

Not intended for use with emergency exit fixtures or emergency exit lights