



35776 - Integrated 2ft LED Glass Tubes

LED8ET8/G/2/835

- Convert your existing linear fluorescent fixture to LED lighting without needing a comprehensive reinstall.
- Each LED tube is outfitted with an internal GE driver.
- The GE integrated LED tubes run on electronic T8 instant-start or programmed start ballasts.
- 66% longer life than LFL (70 000 vs. 30 000 hours)
- No UV
- Easy disposal non-hazardous waste
- Check ballast compatibility at www.gelighting.com/LEDTUBES-ballast-compatibility
- UL Listed
- DLC Listed

PRODUCT PHOTO



GENERAL CHARACTERISTICS

Product Technology	LED
Rated Life (Hours)	70000 h
LED Tube Type	Glass
Environmental Rating	LED_Tube_Glass
10 Digit U	4316835776
Lamp Count	1
Life in Years	45.7 yr
Requested Structure	Sleeve
Estimated Energy Cost per Year	1.02
Bulb Shape	T8

PHOTOMETRIC CHARACTERISTICS

Nominal Initial Lumen per Watt	169
Initial Lumens-nominal	1350 lm
Color Rendering Index-CRI	80
Color Temperature	3500 K

PRODUCT INFORMATION

Product Code	35776
Description	LED8ET8/G/2/835
Alternative Unit Of Measure	EACH
Standard Package Quantity	
Ean UPC	043168357760
Standard Package GTIN	00043168357760
No Of Items Per Sales Unit	
No Of Items Per Standard Package	
Sales Unit	Each
UCC	043168357760
Alternative Unit Of Measure	CASE
Standard Package Quantity	
Ean UPC	043168357760
Standard Package GTIN	10043168357767
No Of Items Per Sales Unit	
No Of Items Per Standard Package	
Sales Unit	Case
UCC	043168357760

DIMENSIONS

Bulb Max Overall Length-MOL	24.0 in
-----------------------------	---------

ELECTRICAL CHARACTERISTICS

Drive Current	45.7
Energy Efficiency Class	yr
Rated power (Watts)	8 W

CAUTIONS & WARNINGS

Caution

Risk of fire

Use only in place of fluorescent lamps specified on label

If the lamp or luminaire exhibits undesirable operation, immediately turn off power, remove lamp from luminaire and contact manufacturer

Direct replacement for 17W/24T8 lamps only

Do not install this lamp in a pre-heat luminaire

This lamp only operates on electronic ballasts

If lamp does not light when luminaire is energized, remove lamp from luminaire and contact lamp manufacturer or qualified electrician

Risk of electric shock

Suitable for damp locations

Not intended for use with emergency exit fixtures or emergency exit lights

