

8538SBG12V02S

NEMA Combination Starter, Type S, 30A fusible disconnect, Size 0, 18A, 3 HP at 240 VAC polyphase, 120 VAC coil, NEMA 1



Principal

Product	Combination Starter
Type	S
Control Circuit Type	Separate control circuit

Complémentaire

Control Circuit Voltage	110 V AC 50 Hz 120 V AC 60 Hz
Starter Type	Non réversible
Number of Poles	3P
Horsepower Rating	3 hp à 200 V AC, 3 phases 3 hp at 230 V AC, 3 phases
Maximum Voltage Rating	600 V AC
Control Units	No control units
Pilot Light	Sans signalisation
Auxiliary Contacts	Sans
Type de surcharge thermique	Melting alloy 3
Disconnect Type	Fusible disconnect switch, type H fusible, 30 A
Taille NEMA	0

Environnement

Enclosure Type	NEMA 1 feuille d'acier peint et with external reset
----------------	---

Emballage

Poids de l'emballage (Kg)	15,839 kg
Hauteur de l'emballage 1	27,432 cm

Largeur de l'emballage 1	33,020 cm
Longueur de l'emballage 1	73,660 cm

Offre de la durabilité

Régulation REACH	Déclaration REACH
Directive RoHS UE	Non conforme
Régulation RoHS Chine	Déclaration RoHS pour la Chine Produit en dehors du périmètre RoHS pour la Chine. Déclaration relative aux substances pour votre information.

Garantie contractuelle

Garantie	18 months
----------	-----------