

# 8538SBG13V02S

NEMA Combination Starter, Type S, 30A fusible disconnect, Size 0, 18A, 5 HP at 600 VAC polyphase, 120 VAC coil, NEMA 1



## Principal

Product	Combination Starter
Type	S
Control Circuit Type	Separate control circuit

## Complémentaire

Control Circuit Voltage	110 V AC 50 Hz 120 V AC 60 Hz
Starter Type	Non réversible
Number of Poles	3P
Horsepower Rating	5 hpà 460 V AC, 3 phases 5 hpà 575 V AC, 3 phases
Maximum Voltage Rating	600 V AC
Control Units	No control units
Pilot Light	Sans signalisation
Auxiliary Contacts	Sans
Type de surcharge thermique	Melting alloy 3
Disconnect Type	Fusible disconnect switch, type H fusible, 30 A
Taille NEMA	0

## Environnement

Enclosure Type	NEMA 1 feuille d'acier peint et with external reset
----------------	---

## Emballage

Poids de l'emballage (Kg)	15,826 kg
Hauteur de l'emballage 1	27,432 cm

Largeur de l'emballage 1	33,020 cm
Longueur de l'emballage 1	73,660 cm

### Offre de la durabilité

Régulation REACH	<a href="#">Déclaration REACH</a>
Directive RoHS UE	Non conforme
Régulation RoHS Chine	<a href="#">Déclaration RoHS pour la Chine</a> Produit en dehors du périmètre RoHS pour la Chine. Déclaration relative aux substances pour votre information.

### Garantie contractuelle

Garantie	18 months
----------	-----------