



GE
Lighting

19382 - GE halogen 500 watt T3 1-pack

Q500T3/CL/CD 5PK

- ☞ GE's specialty bulbs offer innovative solutions for a variety of lighting needs.
- ☞ Uses Halogen technology for a brighter, crisper light
- ☞ 120 volts
- ☞ GE halogen bulbs deliver crisp, white light. This unsurpassed light quality is ideal for adding depth, drama and interest to any room or space. Use GE halogen specialty bulbs to create a dramatic effect
- ☞ Lasts 1.8 years based on 3 hours per day usage
- ☞ T3 shape with Recessed Single Contact (R7s) base for use in outdoor carriage and post lights

Product Photo



GENERAL CHARACTERISTICS

Base Description	Recessed Single Contact
Base Type	Pin/Plug-In
Filament	C-8
Rated Life Hours-nominal	2000 h
Primary Application	Special Service Motion-Sensing & Security
Product Technology	Halogen
Base	R7s
Bulb Shape	T2.5

PHOTOMETRIC CHARACTERISTICS

Nominal Initial Lumen per Watt	22
Initial Lumens-nominal	11100 lm
Color Temperature	3000 K

PRODUCT INFORMATION

Product Code	19382
Description	Q500T3/CL/CD 5PK
Alternative Unit Of Measure	EACH
Standard Package Quantity	60
Ean UPC	043168993807
Standard Package GTIN	00043168193807
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	60
Sales Unit	Each
UCC	043168193825
Alternative Unit Of Measure	CASE
Standard Package Quantity	
Ean UPC	043168993807
Standard Package GTIN	10043168193822
No Of Items Per Sales Unit	
No Of Items Per Standard Package	
Sales Unit	Case
UCC	043168193825
Alternative Unit Of Measure	PACK
Standard Package Quantity	
Ean UPC	043168993807
Standard Package GTIN	00043168193825
No Of Items Per Sales Unit	
No Of Items Per Standard Package	
Sales Unit	Inner Pack
UCC	043168193825

DIMENSIONS

Diameter	0.31 in
Light Center Length	2.25 in

ELECTRICAL CHARACTERISTICS

Burn Position	Horizontal
Input Voltage [nom]	120 V
Rated power (Watts)	500 W

CAUTIONS & WARNINGS

Caution

- Lamp may shatter and cause injury if broken
- Dispose of lamp in a closed container.
- Do not use lamp if outer glass is scratched or broken.

Warning

- Risk of Electric Shock
- Turn power off before inspection installation or removal.

Lamp emits UV radiation which may cause eye/skin injury. RG-3

Avoid exposure of eyes and skin to unshielded lamp.

Risk of Burn

Allow lamp to cool before handling.

Turn power off before installing lamp.

Risk of Fire

Fire Hazard! Do not use in Torchieres or other indoor residential fixtures.

Keep combustible materials away from lamp.

Use in enclosed fixture rated for this product.

Pressurized lamp--unexpected rupture may cause injury, fire, or property damage

Do not exceed 110% of rated voltage.

Do not touch glass with bare hands.

Do not use lamp if outer glass is scratched or broken.

Operate lamp only in specified position -- see instructions.

Use eye protection when handling lamp.

Use in enclosed fixture ra