



Main

Product or Component Type	Full voltage starter
Range of Product	Instakits
Starter Type	Non reversing

Complementary

Control Circuit Voltage	120 V AC 50/60 Hz
Current Rating	80 A
Horsepower Rating	7.5 Hp 120 V AC, 1 phase 15 Hp 240 V AC, 1 phase 25 Hp 208 V AC, 3 phase 30 Hp 230 V AC, 3 phase 60 Hp 460 V AC, 3 phase 60 hp 575 V AC, 3 phase
Maximum Voltage Rating	600 V AC
Auxiliary Contacts	1 NO + 1 NC
Protection Type	Switch-disconnector fuse
Location of connection	Line

Environment

Product Certifications	UL[RETURN]CSA[RETURN]IEC
Enclosure Type	NEMA 1 steel

Ordering and shipping details

Category	22313-CTRS,D-LINE,ENCL (METAL)
Discount Schedule	I11
GTIN	785901427360
Returnability	Yes
Country of origin	MX

Offer Sustainability

Sustainable offer status	Green Premium product
California proposition 65	WARNING: This product can expose you to chemicals including: Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer. For more information go to www.P65Warnings.ca.gov
RECh Regulation	RECh Declaration
RECh free of SVHC	Yes
EU RoHS Directive	Compliant EU RoHS Declaration
Toxic heavy metal free	Yes
Mercury free	Yes

China RoHS Regulation	China RoHS Declaration
RoHS exemption information	Yes
Circularity Profile	No need of specific recycling operations
PVC free	Yes

Contractual warranty

Warranty	18 months
----------	-----------