



# STEEL STUD DEVICE BOXES

## APPLICATION

Steel stud boxes are used in Commercial, Residential and Industrial construction.

## PRODUCT FEATURES

- Unique adjustable mounting strap and patented clip-on tab allow for easy positioning
- Gangable device boxes offer the option of constructing a box to hold two or more devices
- Rugged metallic construction



1102-MSB



1102-MSBU



3102-MSB



3102-MSBU



1104-MSB



1104-MSBUBAR



4204-MSB



4204-MSBU



1504-MSBUBAR



1204-MSB-HV



1104-P\*



7902\*\*

CATALOGUE NUMBER	CAPACITY (CU. IN.)	BRACKET	STUD SIZES	KNOCKOUTS	CABLE CLAMPS
<b>2" x 3" Device Box - 2" Deep - Gangable</b>					
1102-MSB	10.0	MSBS	1-5/8", 2-3/8"	1/2"(4)	-
1102-MSBU	10.0	MSBS	1-5/8", 2-3/8"	-	U
3102-MSB	12.0	MSBS	1-5/8", 2-3/8"	1/2"(4)	-
3102-MSBU	12.0	MSBS	1-5/8", 2-3/8"	-	U
<b>2" x 3" Device Box - 2-1/2" Deep - Gangable</b>					
1104-MSB	12.5	MSB	2-3/8", 3-5/8"	K(2), 1/2"(2)	-
1104-MSBUBAR	12.5	MSB	2-3/8", 3-5/8"	-	U
<b>2" x 3" Device Box - 2-1/2" Deep Power /Communication Box - Gangable</b>					
4204-MSB	12.5	MSB	2-3/8", 3-5/8"	K(4), 1/2"(4)	-
4204-MSBU	12.5	MSB	2-3/8", 3-5/8"	K(2), 1/2"(2)	U
<b>2-1/4" x 3" Device Box - 2-1/2" Deep - Gangable</b>					
1504-MSBUBAR	15.0	MSB	2-3/8", 3-5/8"	-	U
<b>2-1/4" x 3" Device Box - 2-1/2" Deep 347V Box - Gangable</b>					
1204-MSB-HV	15.7	MSB	2-3/8", 3-5/8"	1/2"(2)	-
1104-P*	Partition - For use with 1104 series & 2104, 2, 3, 4-gang metal boxes				
7902**	Foot Extender				

\*Once installed, the box meets Canadian Electrical Code requirements, allowing the installation of devices connected to different power sources within the same box

\*\* Steel stud foot extender. Use with existing MSB foot to facilitate 6" steel stud installation

