



## Hardwire Smoke Alarm with Hush®

Hush® feature ideal to silence nuisance alarm without removing the battery.

### Features:



- **Ionization Technology** – Better at detecting fast flaming fires.



- **120V AC Direct-Wire** – Interconnects with up to 24 units, of which 18 can be initiating.



- **9V Battery Backup (included)** – Continuous protection in case of power failure.



- **Test Button** – Tests circuitry and verifies alarm operation.



- **Hush® Button** – Quickly silences nuisance alarms.

- **Low Battery Indicator** – Warning chirp sounds when battery needs replacement.

- **Interconnectable** – ANY unit that senses a problem automatically triggers ALL units throughout the home immediately, allowing extra time for escape.

### Specifications:

|                     |                                        |
|---------------------|----------------------------------------|
| Product dimensions: | 6" x 6" x 1.5" deep                    |
| Colour / Case Pack  | White / 6 units                        |
| Electrical Rating:  | 120V AC, 60Hz, 60mA, 9V Battery Backup |
| Wiring:             | Quick connect plug with 8" pigtails    |
| Audio Alarm:        | 85dB                                   |
| Temperature Range:  | 40°F (4.4°C) to 100°F (37.8°C)         |
| Humidity Range:     | Up to 85% relative humidity            |
| Sensor:             | Ionization                             |
| Limited Warranty:   | 5 Year                                 |
| Weight:             | 0.40lb                                 |
| UPC:                | 0-47871-40381-3                        |



P1275CA

